

Smart-Tech® Forward Clutch Drum

Part No. 76654-01K


Patent No. 9,562,573

NOTE: Must use thickest OE wave spring (.082" thick — Ford part no. XL3Z-7E085-AA) with Sonnax

kit **76654-01K**. If extra friction capacity is desired, Smart-Tech high capacity forward clutch drum kit **76655-01K** is available from your distributor.

Ford 4R70E, 4R70W, 4R75E, 4R75W, AOD, AODE





1. Disassembly

- a. Before removing OE input shaft, take and record measurement from either end of the input shaft to the drum as shown.
- b. Press input shaft out of OE forward drum.

2. Shaft Assembly

- a. Before pressing OE input shaft into Sonnax forward drum, support the center of the drum as shown.
- b. Use an appropriate high pressure lubricant (STP° oil treatment, 80/90 gear oil, or equivalent) when pressing the parts together.
- c. Press OE shaft into Sonnax drum (**Figure 1**) until shaft-to-drum measurement is equal to that recorded in disassembly step 1A.

3. Clutch Assembly & Clearance

NOTE: Recommended clutch clearance is .010–.014" per friction. Drum will accommodate (5) .061" frictions and (5) .068" steels.

- a. Assemble clutch pack, backing plate, and retaining ring.
- b. Verify clutch clearance by applying slight downward pressure on backing plate, then insert feeler gage between retaining ring and backing plate.
- c. If more or less clearance is required, change the selective thickness retaining ring (**Figure 2**, **page 2**).

©2019 Sonnax Transmission Company, Inc. • A Marmon/Berkshire Hathaway Company



TRANSMISSION PARTS

SMART-TECH® FORWARD CLUTCH DRUM 76654-01K

Instructions

Figure 2

NOTE: To replace an AOD cast forward drum requires updating related components with AODE versions. Update forward clutch pack with AODE style friction, steel & waved plates, backing plate and retaining ring. Additionally, either:

- 1. Machine tips of reluctor from forward drum OR:
- 2. Update sun gear shell and Reverse drum with AODE versions.

Retaining Rings	OE Part Numbers	Thickness
	F3AZ-7D483-A	.052"
	F3AZ-7D483-B	.066"
	F3AZ-7D483-C	.080"
	F3AZ-7D483-D	.094"